

Lighting Your Life Since 1970

Product Specifications - 86094FSBZ		
Job Name:	Job Type:	
Quantity:	Comments	



86094FSBZ

Dover EE 1-Light Outdoor Wall Lantern



Finish Bronze

Lamping

Number of Bulbs	1
Light Type	Fluorescent
Bulb Type	GU24
Max Bulb Wattage	18
Max Fixture Wattage	18
Rated Life	±10,000 Hours
Rated Lumens	±1,355
Color Temp	±2,700 K
Bulb(s)	Included
Light Up/Down	N/A
Beam Spread	N/A
CRI	N/A
Photo Cell Included	No
Ballast/Driver/Transformer	No
Dimmable	No

Glass/Shade
Frosted Seedy

1 lookou coouy	
Measurements	

Canopy Length

mode ar omente	
Width	10.00"
Height	24.50"
Length	N/A
Extension	13"
Back Plate Width	7.00"
Back Plate Height	15.75"
HCO	13.50"
Min Overall Height	0.00"
Max Overall Height	N/A
Hanging Weight	7.37 lbs
Height Adjustable	N/A
Slope	N/A
Chain Length	N/A
Wire Length	N/A
Canopy Width	N/A
Canopy Height	N/A

Product Category

Outdoor Wall Mount

Shipping

Omponig	
Carton Weight	10.34 lbs
Carton Width	12"
Carton Height	28"
Carton Length	17"
Carton Cubic Feet	3.29
Master Pack	1
Master Pack Weight	N/A
Master Pack Width	N/A
Master Pack Height	N/A
Master Pack Length	N/A
Master Cubic Feet	N/A
UPS Shippable	Yes

Certification

Certification		Other	
Safety Rating	Wet	UPC Code	783209089549
Energy Star	Yes	Shades Included	N/A
CA Title 24	Yes	Crystals Included	N/A
CA Title 20	No	Diffuser Included	N/A
ADA	No	Conversion Kit	N/A
Dark Sky	N/A	Material	Die Cast Aluminum

Equivalents

N/A

Incandescent Watts	123
Fluorescent Watts	N/A

Maxim Lighting International and all designs, logos and images © 2015 Maxim Lighting International. All Rights Reserved. Maxim Lighting International reserves the right, at any time, to make changes in the design and/or construction of the product including the discontinuation of product without prior notice. Color may vary from what is pictured above due to limitations inherent to photographic processes.

Always consult a qualified, licensed electrician before installation of any product weighing 35 pounds or more. We recommend that a qualified, licensed electrician do the installation. Always install to a mechanically sound structure.