







INSTALLATION REQUIREMENTS:

Fan must be attached to a securely anchored electrical junction box capable of withstanding a load of at least 50 lbs.

ELECTRICAL REQUIREMENTS:

Requires a grounded electrical supply line of 120 volts AC, 60 Hz, 15 amp circuit.

MOTOR SPECS:

212 x 25 motor is designed for optimal performance with this fan. Fan is Energy Star Rated. 220 VAC, 50 Hz export version available.

BLADES:

A set of five 26" all-weather composite wood blades is included.

CONTROL OPTIONS:

Optional CW1, CW1SW, CW2, CW5 and CWRL4 wall controls and CRL4WH and CRL8TS remote controls (with receiver units) are available—sold separately. Instructions are provided with each control.

LIGHTING OPTIONS:

Optional lighting fitters and light kits are available. See our catalog or visit www.fanimation.com for available lighting options.

DOWNROD OPTIONS:

Fan comes with 1" dia. x 4.5" long downrod. Optional downrods available in 12",18", 24", 36", 48", 60", and 72" lengths. A downrod coupler is available for installations requiring a downrod longer than 72". Fan c an be mounted on a sloped ceiling upto 30°. Most sloped ceiling installations require a downrod longer than the standard 6" downrod. Call technical support for more information.

LOCATION USE:

Fan is rated for dry, damp and wet locations.

| | Α | В | | | |
|--------------------|--------|--------|--|--|--|
| Fan w/4.5" downrod | 14.62" | 13.22" | | | |
| Fan w/12" downrod | 22.12" | 20.72" | | | |
| Fan w/18" downrod | 28.12" | 26.72" | | | |
| Fan w/24" downrod | 34.12" | 32.72" | | | |
| Fan w/36" downrod | 46.12" | 44.72" | | | |
| Fan w/48" downrod | 58.12" | 56.72" | | | |
| Fan w/60" downrod | 70.12" | 68.72" | | | |
| Fan w/72" downrod | 82.12" | 80.72" | | | |

| Available Finishes | | | | | |
|------------------------|--------------|----------------------|--|--|--|
| Fan / Housing Assembly | | Blades - Traditional | | | |
| ΑZ | Aged Bronze | Dark Cherry | | | |
| SN | Satin Nickel | Mahogany | | | |
| WH | White | White | | | |

| Airflow / Energy Efficiency Info (120V) | | | | | | | | |
|---|---------|------|-------------|------|-------|--|--|--|
| Fan Speed | Max RPM | CFM | CFM / Watts | Amps | Watts | | | |
| High | 159 | 8963 | 106 | 0.73 | 84.3 | | | |
| Med | 115 | 6596 | 132 | 0.56 | 49.8 | | | |
| Low | 74 | 4001 | 182 | 0.37 | 22.0 | | | |